

Alarm program (code 3368) 27.03.2007

From 01.09.2017, all modules have 5-digit program numbers Chenged blinking-out CAN BUS connection status: After showing 5 digits of the program number, the module will blink-out connection status of 6 CANs, Number of LED blinks for each CAN BUS:

1 blink - CAN has already been connected but now it is not receiving any data;

2 blinks - CAN is connected and is receiving data at the moment;

3 blinks - CAN disconnected, but requires connection;


4 blinks - CAN not supported, no connection required.


Changing the program number:

Changing the program number:

Press and hold the button until the LED starts to blink, then release the button; the LED will start counting (from 1 to 9) to indicate the first of five digits of the Program number; after the right number of blinks, hold down the button until the LED starts to blink again, then release the button. Program the next digits of the Program number in the same way. The LED will blink 10 times after completing programming successfully. Then the main unit will restart, which will be signaled by a double blink of the LED

Checking the program number: Press the button briefly. Initially the LED of the main unit will blink out 5-digit of the pre-set Program number and then the connection status of the connected CAN BUSes





Version: 21xxxxxx

year: **17** → rev03